



Audio and power input provided on barrier strip (on Stand Alone unit only)

Speaker Outputs

JU6 Mute  
Short these pins together to mute

J7 Left speaker

J8 Right speaker

JU3  
Install for stereo operation

JU6 and JU8 Power limit

- Full power
- Medium power
- Low power

Level control

Signal Present LED

Direct power in +/- 15 volts DC

Speaker right  
Power ground  
Speaker left

Right +  
Right -  
Shield ground  
Left -  
Left +

2 StudioHub+ RJ45 Input and power in connectors in parallel (on non Stand Alone unit only)

JU1  
Install to connect shield ground to power ground

JU2  
Install to connect shield ground to chassis ground

JU4, JU5 Gain Straps  
 Unity  
 +10dB  
 +20dB

JU7 Mono - Stereo jumper  
 Stereo operation  
 Mono operation

Left output is a mix of left and right inputs. Right output is muted

### StudioHub+ Monitor Amp Plate

Part # SH-AMP w/o Speaker

Part # SH-AMPSPKR w/Speaker

Part # SH-AMPSA w/o Speaker Stand Alone

Part # SH-AMPSPKRSA w/Speaker Stand Alone

Stand Alone Units include barrier strip & power supply (wall wart)

